IN THE UNITED STATES PATENT AND TRADEMARK OFFICE

ATTORNEY DOCKET NO.:   1017.P051USC1

TITLE:

METHOD AND APPARATUS FOR ULTRASONIC LASER TESTING

INVENTORS:

Thomas E. Drake, Jr.
Mark A. Osterkamp

SUBMITTED BY:

Koestner Bertani, LLP
4201 W. Parmer Lane
Suite A-100
Austin, Texas 78727
(512) 399-4100
(512) 692-2529 (Fax)

1

METHOD AND APPARATUS FOR ULTRASONIC LASER TESTING

RELATED APPLICATIONS

5   This application claims the benefit of U.S. Provisional Application No. 60/091,240 filed on 30 June 1998. Additionally, this application incorporates by reference the prior of U.S. Provisional Application No. 60/091,229 filed on 30 June 1998 entitled "METHOD AND APPARATUS FOR DETECTING ULTRASONIC SURFACE DISPLACEMENTS
10   USING POST-COLLECTION OPTICAL AMPLIFICATION" to Thomas E. Drake.

TECHNICAL FIELD OF THE INVENTION

15   The present invention relates generally to an apparatus and method of non-destructive evaluation of materials, and more particularly, to an apparatus and method of processing optical information to detect ultrasonic surface displacements through the use of at
20   least one laser to perform a non-destructive evaluation of a material.

BACKGROUND OF THE INVENTION

In recent years, the use of advanced composite
structures has experienced tremendous growth in the
aerospace, automotive, and many other commercial
industries. While composite materials offer significant
improvements in performance, they require strict
quality control procedures in the manufacturing
processes. Specifically, non-destructive evaluation
("NDE") methods are required to assess the structural
integrity of composite structures, for example, to
detect inclusions, delaminations and porosities.
Conventional NDE methods, however, are very slow,
labor-intensive, and costly. As a result, testing
procedures adversely increase the manufacturing costs
associated with composite structures.

Various methods and apparatuses have been proposed
to assess the structural integrity of composite
structures. One method to generate and detect
ultrasound using lasers is disclosed in U.S. Patent
5,608,166, issued March 4, 1997, to Monchalin et al.
(the "'166 Patent"). The '166 Patent discloses the use of
a first modulated, pulsed laser beam for generating
ultrasound on a work piece and a second pulsed laser
beam for detecting the ultrasound. Phase modulated
light from the second laser beam is then demodulated to
obtain a signal representative of the ultrasonic motion
at the surface of the work piece. A disadvantage
associated with this approach is that the first pulsed
laser beam must be modulated. Other U.S. Patents issued
to Monchalin et al. and relating to the subject matter
of ultrasonic material testing include the following:

U.S. Patent No.	Title	Issue Date
5,608,166	Generation and Detection of Ultrasound with Long Pulse Lasers	Mar. 4, 1997
4,966,459	Broadbank Optical Detection of Transient Motion from a Scattering Surface	Oct. 30, 1990
5,131,748	Broadbank Optical Detection of Transient Motion from a Scattering Surface by Two-Wave Mixing in a Photorefractive Crystal	Jul. 21, 1992
5,402,235	Imaging of Ultrasonic-Surface Motion by Optical Multiplexing	Mar. 29, 1995
4,633,715	Laser Heterodyne Interferometric Method and Apparatus for Measuring Ultrasonic Displacements	Jan. 6, 1987
5,080,491	Laser Optical Ultrasound Detection Using Two Interferometer Apparatuses	Jan. 14, 1992
5,137,361	Optical Detection of a Surface Motion of an Object Using a Stabilized Interferometric Cavity	Aug. 11, 1992
4,426,155	Method and Apparatus for the Interferometric Wavelength Measurement of Frequency Tunable C.W. Lasers	Jan. 17, 1984

U.S. Patent No.	Title	Issue Date
5,608,166	Generation and Detection of Ultrasound with Long Pulse Lasers	Mar. 4, 1997
4,820,981	Method and Apparatus for Measuring Magnetic Losses in Ferromagnetic Materials Based on Temperature Modulation Measurements	Apr. 11, 1989
4,659,224	Optical Interferometric Reception of Ultrasonic Energy	Apr. 21, 1987
4,607,341	Device for Determining Properties of Materials from a Measurement of Ultrasonic Absorption	Aug. 19, 1986

Although these patents describe operable techniques for optically detecting transient motion from a scattering surface, which techniques are useful for ultrasonic composite materials non-destructive test and evaluation, these techniques have numerous failings.

To begin, none of the Monchalin and other known techniques provide the ability to perform with high signal-to-noise-ratios (SNR) at large distances from typically very dark composite materials using small aperture high-speed optical scanning methods. The ability to operate in such a mode has the distinct advantage of increasing the optical scan area coverage and providing substantially improved depth-of-field

thereby eliminating the need for active focusing
mechanisms.

Other known techniques do not posses the desirable
feature of removing common-mode noise from the laser
signals using a fully self-referenced interferometric
configuration that uses all of the available light
without the use of separate stabilization measurements.

Another limitation associated with the Monchalin
and other known apparatuses relates to their inability
to operate at very high scan rates and process
ultrasonic data in real-time. This limitation makes
such apparatuses only marginally useful for testing and
evaluating composite materials.

Other limitations associated with existing
apparatuses relate to general inflexibility of such
apparatuses, which may hold all distances low, result
in small depth of field performance and only minimal
extraction of information from the back scattered
signals. These limitations make industrial application
of the ultrasonic testing method generally impractical.

SUMMARY OF THE INVENTION

The present invention provides an apparatus and method for generating and detecting ultrasonic surface displacements on a remote target that substantially eliminates or reduces disadvantages and problems associated with previously developed laser ultrasonic systems and methods.

More specifically, the present invention provides a method and system for generating and detecting ultrasonic surface displacements on a remote target. The system includes a first pulsed laser to generate a first pulsed laser beam. The first pulsed laser beam produces ultrasonic surface displacements on a surface of the remote target. A second pulsed laser generates a second pulsed laser beam coaxial with said first pulsed laser beam to detect the ultrasonic surface displacements on the surface of the remote target. Collection optics to collect phase modulated light from the second pulsed laser beam either reflected or scattered by the remote target and optionally optically processed to increase the light intensity. An interferometer to process the phase modulated light and generate at least one output signal. A processor for processing the at least one output signal obtains data representative of the ultrasonic surface displacements on the surface of the remote target.

In another embodiment, a method for ultrasonic laser testing in accordance with the invention comprises using a first pulsed laser beam to generate ultrasonic surface displacements on a surface of a remote target. A second pulsed laser beam coaxial is used with the first pulsed laser beam to detect the

ultrasonic surface displacements on the surface of the
remote target collecting phase modulated light from the
second pulse laser beam either reflected or scattered
by the remote target also occurs, processing the phase
modulated light to obtain data representative of the
ultrasonic surface displacements on the surface of the
remote target.

A technical advantage of the present invention is
that a method for ultrasonic laser testing is provided.
The personal invention provides rapid, non-contact, and
non-destructive inspection techniques that can be
applied to complex composite structures. The present
invention provides a flexible, accurate and cost
effective method for inspecting complex composite
structures. The present invention is able to rapidly
scan and test large-sized composite structures. The
present invention is able to inspect at angles off
normal (i.e., up to $\pm$ 45 degrees). The present
invention does not require expensive fixturing to test
composite structures. The present invention does not
require the shape of the part to be known prior to
testing. The present invention does not require access
to both sides of a composite structure to test it for
defects.

BRIEF DESCRIPTION OF THE DRAWINGS

For a more complete understanding of the present invention, the objects and advantages thereof, reference is now made to the following descriptions taken in connection with the accompanying drawings in which:

FIGURE 1 illustrates the use of a generation laser beam and a detection laser beam coaxial therewith;

FIGURE 2 is a block diagram showing the basic components of an apparatus for performing ultrasonic laser testing;

FIGURE 3 presents a large aperture optical scanner;

FIGURE 4 presents a small aperture optical scanner;

FIGURE 5A presents a gantry mounted optical test apparatus with an internal calibration unit;

FIGURE 5B presents a gantry mounted optical test apparatus with an internal calibration unit;

FIGURE 6 is a timing diagram for a non-flat detection pulse and a generation pulse;

FIGURE 7 is a timing diagram for a flat detection pulse and a generation pulse;

FIGURE 8 is a modified, single cavity confocal Fabry-Perot type interferometer;

FIGURE 9 is a modified, dual cavity confocal Fabry-Perot type interferometer;

FIGURE 10 illustrates the relationship between the reflected and transmitted light, relative to the total amount of light which reaches a cavity;

FIGURE 11 is a signal-to-noise ratio plot as a function of optical power;

FIGURE 12A is a signal response analysis as a
function of frequency;

FIGURE 12B is a phase response analysis for the
signal presented in FIGURE 12A;

FIGURE 13A is a noise response analysis as a
function of frequency;

FIGURE 13B is a phase response analysis for the
information presented in FIGURE 13A;

FIGUREs 14(A and B) are a response analysis and the
phase response for a signal that has been modified to
permit cancellation of common mode laser noise;

FIGURE 15 presents an optical interferometer with
separate detectors and processors;

FIGURE 16 is an electrical schematic for an
improved detector; and

FIGURE 17 is a frequency response for the
electrical schematic of FIGURE 16.

DETAILED DESCRIPTION OF THE INVENTION

Preferred embodiments of the present invention are illustrated in FIGUREs 1 through 17 of the drawings, like numerals being used for like and corresponding
5   parts of the various drawings.

FIGURE 1 illustrates an incoming laser beam which represents a generation laser beam 111 and a coaxial detection laser beam 121 upon a remote target 150. Generation laser beam 111 causes thermoelastic
10   expansion in the target 150 in the form of ultrasonic surface deformations, which deformations modulate, scatter and reflect detection laser beam 121, represented by the phase-modulated light 131 directed away from target 150.

15   FIGURE 2 illustrates in block diagram form the basic components of an apparatus 200 for performing ultrasonic laser testing. Apparatus 200 comprises a generation laser 210, a detection laser 220, an interferometer 230, an optional optical processor 235,
20   an optical scanner 240, collection optics 250, systems controller 260, and data acquisition and processing apparatus 270. Generation laser 210 and detection laser 220 generate a generation laser beam 111 and a detection laser beam 121, respectively, which are
25   directed by optical scanner 240 upon a target 150, which is typically a composite material. The generation laser 210 produces a compressional ultrasonic wave in the material normal to the surface of the target 150. The compressional ultrasonic wave is the result of
30   thermoelastic expansion of the composite material as it absorbs generation laser beam 111.

The generation laser 210 must be of a frequency

that is readily absorbed into the surface of target 150 without causing ablation or breaking down the target material, and it must be of the appropriate pulse duration to induce ultrasonic surface deformations. For

5   example, a transverse-excited atmospheric ("TEA") CO_2 laser can be used to produce a 10.6 micron wavelength beam for a 100 nanosecond pulse. The power of the laser must be sufficient to deliver, for example, a 0.25 joule pulse to the target, which may require a 100 watt

10   laser operating at a 400 Hz pulse repetition rate. The generation laser should be absorbed as heat into the target surface thereby causing thermoelastic expansion without ablation.

        The detection laser 220 must be of sufficient pulse

15   duration to not induce ultrasonic surface displacements. For example, a Nd:YAG laser can be used. The power of this laser must be sufficient to deliver, for example, a 100 milli-joule, 100 micro-second pulse, which may require a one kilo-watt laser.

20   FIGURE 3 illustrates a large aperture optical scanning configuration with an integrated distance ranging unit. Generation laser beam 111 is focused by generation laser focus optics 310 through a first optical lens assembly 315 which is transmissive to

25   generation laser beam 111. Reflective surface 335 then directs generation laser beam 111 upon large aperture scanner 340 which, in turn, directs said beam 111 upon a surface of target 150, which induces an ultrasonic wave therein.

As shown in FIGURE 3, detection laser beam 121 is directed by fiber optics into detection laser focus optics 320, which focuses laser beam 121 through a second optical lens 325 which is transmissive to

5   detection laser beam 121. Detection laser beam 121 is reflected off first optical lens 315 and emerges coaxial with generation laser beam 111. First optical assembly 315 and second optical assembly 325 act collectively to form a beam combiner or beam mixer.

10   Detection laser beam 121 is then reflected along with generation laser beam 111 upon a turning mirror or a reflective surface 335, which then directs detection laser beam 121 upon large aperture scanner 340 which, in turn, directs said beam 121 upon the surface of

15   target 150. Detection laser beam 121 interacts with the ultrasonic waves present in the surface of target 150, and is reflected as phase modulated light 131. Some of the phase modulated light is captured by large aperture scanner 340 and is directed upon large aperture

20   collector 350. Large aperture scanner 340 is generally of the single-mirror two-axis gimbal construction with each axis driven via a motor and gear assembly. Large aperture collector 350 may be of a Cassegrain-type reflective optic, comprised of a primary reflective

25   surface 355 which focuses light upon a secondary reflective surface 345, which in turn, collects the light and focuses it into a fiber optic carrier.

        FIGURE 3 also illustrates the integrated optical ranging unit 330 which directs a ranging laser beam 331

30   upon optical lens 325 which reflects said laser beam 331 upon first optical lens 315. Ranging laser beam 331 emerges coaxial with generation laser beam 111 and

detection laser beam 121. Ranging laser beam 331 is
then reflected along the same path as detection laser
beam 121 and also is reflected from the surface of
target 150. Some of the reflected ranging laser is
5   captured by large aperture scanner 340 and directed
backwards upon the same path which it traveled to reach
target 150. Scanner 340, collection optics 345 and 355
are generally defined as of the large aperture type for
beam clear apertures larger than approximately 75mm for
10   distances to the target in the 1000mm to 4000mm range.
Optical ranging unit 330 is able to determine from the
reflected light the distance between the surface of the
target 150 being illuminated and the scanning
apparatus. Because optical ranging unit 330 both
15   transmits and receives light of the same frequency, it
is described as a self-contained ranging apparatus. It
is important to know the distance by which the surface
being illuminated is located from the scanner so that a
topographical contour can be created for target 150 and
20   correlated to the optical data being collected.
Generally, this correlation is recorded on a point-by-
point basis.
         FIGURE 4 illustrates a small aperture optical
scanning configuration with an integrated distance
25   ranging unit. Small aperture is generally defined, in
this application, for clear apertures less than 75mm
for target distances between 1000mm and 4000mm. The
operation of the small aperture configuration is
similar to that of the large aperture optical scanning
30   configuration previously discussed with a slight
rearrangement of the optical elements to accommodate
the laser beams through the smaller apertures.

Generation laser beam 111 is focused by generation
laser focus optics 310 through a first optical element
415 to small aperture scanner 440, where in the optical
element 415 is transmissive to generation laser beam
5   111. Small aperture scanner 440, in turn, directs said
beam 111 upon a surface of target 150, which induces an
ultrasonic wave therein. Small aperture scanner 440 is
generally of two-mirror construction with each mirror
mounted on orthogonal oriented high-speed
10 galvanometers.

As shown in FIGURE 4, detection laser beam 121 is
directed by fiber optics into detection laser focus
optics 320, which directs laser beam 121 to a small
reflective turning mirror 445 and through optical
15 element 435, which is transmissive to detection laser
beam 121. Detection laser beam 121 is reflected off
first optical element 415 and emerges coaxial with
generation laser beam 111. Reflective turning mirror
455 is generally of elliptical profile so as to produce
20 a small circular diameter exactly matching detection
laser beam 121 when operated at 45 degrees angle of
incidence, and thereby obscuring a minimal amount of
collection optic 450. First optical element 415, second
optical element 425, and third optical element 435
25 collectively act to form a beam combiner or beam mixer.
Detection laser beam 121 is then reflected along with
generation laser beam 111 upon small aperture scanner
440 which, in turn, directs said beam 121 upon the
surface of target 150. Detection laser beam 121
30 interacts with the ultrasonic waves present in the
surface of target 150, and is reflected as phase-
modulated light 131. Some of phase modulated light 131

is captured by small aperture scanner 440 and is
reflected off first optical element 415, through third
optical element 435, and reflected off second optical
element 425 into small aperture collector 450. Optical
5   element 445 will, by proper design, obscure a minimal
portion of the light captured by scanner 440.

FIGURE 4 also illustrates the integrated optical
ranging unit 330 which directs a ranging laser beam 331
upon third optical element 435 which reflects laser
10   beam 331 upon first optical element 415. Ranging laser
beam 331 emerges coaxial with generation laser beam 111
and detection laser beam 121. Ranging laser beam 331 is
then reflected along the same path as detection laser
beam 121 and also gets reflected from the surface of
15   target 150. Some of the reflected ranging laser is
captured by small aperture scanner 440 and directed
backwards upon the same path which it traveled to reach
target 150. Optical ranging unit 330 is able to
determine from the reflected light the distance between
20   the scanning apparatus and the surface of the target
150 being illuminated. The distance between the
scanning apparatus and the surface being illuminated is
used to create a topographical contour of the target
150 being scanned, and is correlated to the optical
25   data being collected. Generally, this correlation is
recorded on a point-by-point basis.

FIGURE 5A illustrates a portion of a laser
scanning and test apparatus 500, referred to as "scan
head 500", that is typically, although not exclusively,
30   mounted to a gantry positioning system (GPS) capable of
indexing said apparatus throughout a Cartesian work
volume defined by {x,y,z}. Generation laser 110 may be

remotely located on the GPS, or alternatively ground
mounted and directed along the x and y axis, and
eventually directed concentric with the z-mast assembly
through gantry mounting ring 510. Another embodiment of
said invention would allow delivery of generation laser
210 laser beam 111 through an optical fiber. Fiber
optic delivery of laser beam 111 would allow generation
laser 210 to be remotely located or optionally mounted
within scan head 500. Scan head 500 can be rotated
concentric to the z-axis defined as theta-1 to
reposition the orientation of the optical table
mounting bracket 530 and optical table 535. Cable tray
520 provides electrical, optical, and other connections
to 500 allowing 360-degree rotation of theta-1. Bracket
540 attaches motor 550 to optical table 535. Motor 550
rotates optical scanner 440 via torque tube 555
concentric with the optical axis, defined as the theta-
2 axis. Slip ring 560 provides electrical connections
between VME chassis 590 and components mounted to the
theta-2 axis, including optical scanner 440, scanner
shutter 565, and remote video camera 570. Scanner
shutter 560 protects optical scanner 440 from dust
contamination when not in use. Remote video camera 570
provides the operator at a distant location a view
nearly aligned with the center view of scanner 440.
Detection laser light 121 is collected from a remote
composite surface located some distance D from the
small-aperture optical scanner 440 and is reflected by
element 415, transmitted by element 435, and is
minimally obscured by mirror 445. Next 121 is directed
by mirror 425, and other turning mirrors, onto small-
aperture collector 450, and subsequently coupled into

the collection fiber optic. This collection fiber is
typically coupled to a post-collection optical
amplifier 235 (FIGURE 2) prior to processing by
interferometer 230.

5   Motorized mirror mount 580 provides a method to
redirect the optical path for all of the laser beams
beyond optical element 415 but prior to optical scanner
440. Said redirected beams follow a path along a series
of reflective turning mirrors 581, 582, 583, 584, 585,

10   and 586 to an internal far-field calibration module
587, the number of turning mirrors is only
representative of the desired function, where the
actual number could be more or less. Tuning mirror 581,
for example, would have an integrated near field

15   adjustable aperture to establish a permanent alignment
position to be used in conjunction with the internal
far-field calibration module 587. Far-field calibration
module 587 is located a distance from optical element
415 to be representative of a typical distance to a

20   target following the standard path through optical
scanner 440. Internal far-field calibration and
diagnostic module 587 may contain, as example, devices
to monitor the power and alignment of each laser, small
targets representative of typical testing materials,

25   and devices to assist in the characterization of new
materials over a variety of incident angles. As an
example, information derived from the internal far-
field calibration and diagnostic module 587 could be
used to align the generation laser beam 111 to the

30   desired optic axis via motorized reflective tuning
mirrors 588 and 589. Such an operation may be necessary
to correct for small beam delivery errors created by

the remote free-space delivery of beam 111 along the
movable axis {x,y,z,theta-1}. Other turning mirrors,
not explicitly specified in FIGURE 5a, may also
incorporate motorized positioning features similar to
5   588 and 589 as required to allow a fully automated
alignment and calibration procedure to be executed
under computer control. All alignment procedures are
generalized in that the motorized mirror nearest the
far-field calibration module is adjusted for proper
10 alignment, then the motorized mirror farthest from the
near-field aperture is adjusted for alignment. This
procedure is continued in an iterative manner until an
allowable amount of positioning error is reached.
      FIGURE 5B illustrates scan head 500 in a
15 perspective view with the addition of the detection
laser mounted to the rear surface of optical table 535.
In this configuration the detection laser beam 121 may
be optionally fiber optic coupled to the front side of
optical table 535 or directly coupled via turning
20 mirrors. Fiber delivery via detection laser focusing
optics 320 has the advantage of improved beam pointing
stability due to the decoupling of any small beam
pointing errors in laser 220. The peak power of laser
220 will limit the distance that fiber optics can be
25 used to deliver beam 121 due to stimulated Brillouin
scattering (SBS) effects. SBS threshold is dependent on
the fiber diameter, fiber length, laser pulse duration,
and laser peak power. For example, a Nd:YAG laser with
a 100 microsecond pulse duration producing hundreds of
30 watts of peak power would be limited to fiber lengths
below 10 meters for 100microm fiber diameters.
      FIGURE 6 illustrates the timing relationship

between the generation and detection laser pulses. Detection laser beam 121 is fired at $t=t_0$. The magnitude of detection laser beam 121 rises to a maximum before falling off. The pulse width of

5   detection laser beam 121 and generation laser beam 111 are illustrated in FIGURE 6 as 100 micro-seconds and 100 nS, respectively, though the pulse widths may be varied. Generation laser beam 111 is ideally fired when detection laser beam 121 is at or near its maximum

10   peak, which time delay after t_0 is represented by t_{delay}. When testing a target 150, detection and generation pulses are typically repeated on a periodic basis, for example, with a frequency of 100 Hz or even 1000 Hz where optical scanner 440 indexes the laser beam to a

15   new position between each pulse. Ideally, the time

delay Δ between subsequent pulses is sufficient to allow ultrasonic activity to dissipate so that there is no overlap between subsequent tests.

        FIGURE 7 illustrates that detection laser beam 121

20   may also be a flat pulse beam as shown in FIGURE 7. By using a flat pulse detection laser, the time delay t_{delay} between detection laser beam 121 and generation laser beam 111 can be reduced because a flat pulse beam requires less time to reach its maximum intensity.

25   FIGURE 8 illustrates a confocal Fabry-Perot interferometer which is stabilized using only the input signal. The self-referenced feature is unlike many prior art designs which utilizes a portion of the generation laser beam for stabilization. In FIGURE 8

30   incoming light from a fiber optic input is directed through a first lens 810 onto a first reflective surface 850, off a second reflective surface 860,

through a first polarized beam splitter 840, through a
quarter-wavelength plate 870, and into a first cavity
895. First cavity 895 has a confocal lens structure
comprised of a first spherical mirror 875 and a second

5   spherical mirror 885. When the incoming light passes
through first polarized beam splitter 840, only the
horizontally-polarized component is passed, which
component becomes circularly polarized (p-state) once
it passes through quarter-wavelength plate 870.

10   The confocal lens structure is designed so that
the incoming light falls upon itself after four passes
through the cavity. First spherical mirror 875 and
second spherical mirror 885 each have the same radius
of curvature "r", and when the two mirrors are spaced

15   from each other by this radius "r", the mirrors are
said to be in a confocal position, and the light is
said to be "re-entrant light" because it falls back
upon itself after four passes across the mirrors. First
spherical mirror 875 and second spherical mirror 885

20   are partially transmissive, meaning they pass light as
well as reflect light. For example, the said mirrors
may be 95% reflective and 57% ignoring absorption and
scattering losses, transmissive (i.e. permitting 55% of
the light to pass through the mirror).

25   Some of the incoming light is transmitted through
second spherical mirror 885. A third lens 830 focuses
the light that is transmitted through second spherical
mirror 885 upon transmission-mode detector 890 or
optionally an optical fiber attached to transmission

30   mode detector 890, where it can be quantified by
variable V_{r1}. Second spherical mirror 885 also reflects

a portion of the light back upon first spherical mirror
875, where again, some of the light is passed through
spherical mirror 875, and through quarter-wavelength
plate 870. When the reflected light passes through
5   quarter-wavelength plate 870 for the second time, the
polarization of the light is changed again, and in this
case, becomes vertically polarized (s-state). The
vertically polarized, reflected light is then rejected
by first polarized beam splitter 840 and is reflected
10   upon second lens 820, which focuses the reflected light
upon a reflection-mode detector 880 or optionally an
optical fiber attached to reflection-mode detector 880,
where it can be quantified by variable V_{R1}.

       It is possible to vary the amount of light which
15   is transmitted through the cavity relative to the
amount of light which is reflected back through the
cavity, that is, vary V_{T1} relative to V_{R1}. One way to
vary this relationship is by changing the frequency of
the incoming light. An alternative way to vary the
20   relationship is by adjusting the distance between first
spherical mirror 875 and second spherical mirror 885.
In a confocal relationship, this distance is nominally
the radius of curvature "r". One way to vary this
distance is to mount at least one of the spherical
25   mirrors on adjustable mounts. In FIGURE 8, first
spherical mirror 875 is mounted on piezoelectric mounts
876, which permits the lineal displacement of first
spherical mirror in a controlled fashion using a
piezoelectric device. The design of the present
30   invention permits the distance between first spherical
mirror 875 and second spherical mirror 885 to be

increased by an additional amount "n", representing a
small sub-wave length lineal displacement of first
spherical mirror 875 by the piezoelectric device. Thus,
the distance between the spherical mirrors can be

5   represented by formula r+n. In FIGURE 8, second
spherical mirror 885 is mounted on manual mounts 886 to
permit manual adjustment. Manual mounts 886 permit the

cavity to be adjusted during setup for a "rough"
adjustment to establish the correct confocal length,

10 where for example, the length r must be within
200microns of the desired length for a 1000mm cavity.
This feature when combined with the fine tuning using
the piezoelectric device, provides the invention with
significant flexibility.

15   FIGURE 9 illustrates a confocal Fabry-Perot
interferometer having two cavities, again which is
stabilized using only the input light. The first cavity
895 in this configuration functions the same as the
cavity described in connection with FIGURE 8, and

20 therefore, only the differences will be described here.
     In FIGURE 9 incoming light is directed onto first
polarized beam splitter 840, where the light is divided
into its horizontally-polarized (p-state) component and
its vertically-polarized (s-state) component. One

25 polarization of light is directed into first cavity
895, while the other polarization is directed into a
second cavity 995. To be consistent with FIGURE 8, the
horizontal component is directed into first cavity 895
while the vertical component is reflected upward where

30 it will be ultimately diverted into second cavity 995.
The vertically polarized light travels from the first

polarized beam splitter 840 to a second polarized beam splitter 940, where the light is reflected through a quarter-wavelength plate 970. The vertically-polarized light becomes circularly polarized once it passes

5   through quarter-wavelength plate 970. The light is subsequently delivered into second cavity 995, where as in the first cavity 895, some of the light is transmitted through while some is reflected back.

As in the first cavity, first spherical mirror 975

10   and second spherical mirror 985 each have the same

radius of curvature "r"(which is the same radius of curvature as in the first cavity 995), such that when the two mirrors are spaced from each other by this

radius "r", the mirrors refocus incoming light upon

15   itself after it travels four passes through the cavities (i.e., two round trips).

The light that is transmitted through second spherical mirror 985 is focused by third lens 930 upon transmission mode detector 990 or optionally an optical

20   fiber attached to transmission-mode detector 990, where it can be quantified by variable V_{T2}. Second spherical mirror 985 also reflects a portion of the light back upon first spherical mirror 975, where again, some of the light is passed through spherical mirror 975, and

25   through quarter-wavelength plate 970. When the reflected light passes through quarter-wavelength plate 970 for the second time, the polarization of the light is changed again, and in this case, becomes horizontally polarized. The horizontally polarized,

30   reflected light then passes through polarized beam splitter 940, and is focused by second lens 920 upon

reflection-mode detector 980 or optionally an optical
fiber attached to reflection mode detector 980, where
the reflected light can be quantified by variable V_{R2}.

It is possible to vary the amount of light which
is transmitted or passes through each of the cavities
relative to the amount of light which is reflected back
through each of said cavities, that is, vary V_{T1}
relative to V_{R1}, and vary V_{T2} relative to V_{R2}. One way to
vary this relationship is by changing the frequency of
the incoming light. An alternative way to vary the
relationship is by adjusting the distances between
first spherical mirrors 875 and 975 and second
spherical mirror 885 and 985, respectively. In a
confocal relationship, each of these distances is
nominally the radius of curvature "r". One way to vary
this distance is to mount at least one of each pair of
spherical mirrors on adjustable mounts. In FIGURE 9
each of first spherical mirrors 875 and 975 is mounted
on piezoelectric mounts 876 and 976, respectively,
which permits the sub-wavelength lineal displacement of
first spherical mirrors 875, 975 in a controlled
fashion using piezoelectric devices. The design of the
present invention permits the distances between first
spherical mirrors 875, 975 and second spherical mirrors
885, 985, respectively, to be increased by additional
amounts "ε_1"and "ε_2", representing the lineal
displacements of each of first spherical mirrors 875,
975 by piezoelectric means. Thus, the distances between
the spherical mirrors within each cavity can be
represented by formula $r+\varepsilon_1$ and $r+\varepsilon_2$. In FIGURE 9, each
of second spherical mirrors 885, 985 is mounted on

manual mounts 886, 986, respectively, to permit manual
adjustment. Manual mounts 886, 986 permit the cavity to
be adjusted during setup for a "rough" adjustment to
within a few hundred microns of the true confocal

5   length, which when combined with the fine tuning using
the piezoelectric means, provides the invention with
significant flexibility.

FIGURE 10 demonstrates the relationship between
the amount of light transmitted through a confocal

10   cavity ("V_T"), the amount of light reflected back
through the cavity ("V_R"), and the fine tuning
adjustment represented by ε. The normalized intensity
of the transmitted and reflected light can be described
in equation form by first defining two general complex

15   (i.e. containing imaginary terms) functions as follows:

$$\beta(x) = \frac{T}{1 - R^2 e^{-ix}}$$

$$\gamma(x) = 1 - R\beta(x)e^{-ix}$$

where R is the mirror reflectivity and T is the mirror

20   transmission usually given by T = 1-R if absorption and
scattering effects are ignored. Now the intensity of
the light can be written as:

$$transmission = (1 - R^2)\left|\beta\left(2\pi\varepsilon\frac{4}{\lambda}\right)\right|^2$$

$$reflection = R\left[\left|\gamma\left(2\pi\varepsilon\frac{4}{\lambda}\right)\right|^2 + \left|\beta\left(2\pi\varepsilon\frac{4}{\lambda}\right)\right|^2\right]$$

where epsilon is the change in the cavity length from
the confocal length r and lambda is the laser

5   wavelength, and the magnitude operations on the complex
function makes the results real expressions. These two
equations will produce FIGURE 10. Where the reflected
light curve 1020 represents the proportion of total
light that is reflected back through the cavity,

10   (normalized reflection = $V_R/(V_R+V_T)$), which figure is
always between 0.5 and 1.0. Transmitted light curve
1080 represents the proportion of total light that is
transmitted through the cavity, (normalized
transmission = $V_T/(V_R+V_T)$), which figure is always

15   between 0.0 and 0.5. The sum of V_R and V_T represents the
total amount of light that reaches the cavity.
Reflected light curve 1020 and transmitted light curve
1080 are each plotted as a function of ε/S, and V_R, and
V_T are both equal when ε/S is equal to 0, 0.25, and 0.5,

20   or more generically, when ε/S = n/4, n being a whole
number. Thus it is apparent that the piezoelectric
mirror mounts 876 and 976 must move a minimum of $\lambda/4$ to
provide a sufficient tuning range.
     While FIGURE 10 is plotted for V_R, and V_T

25   (normalized, of course, with respect to the total
amount of light), a similar relationship holds with

respect to the variables V_{R1}, V_{T1}, V_{R2}, and V_{T2} which were discussed in connection with FIGUREs 8 and 9. While ε_1 and ε_2 are generally independent of each other in the two confocal cavity design, ε_1 and ε_2 are generally adjusted to maintain the same relationships between reflected and transmitted light in each of the cavities. For example, the cavities can be adjusted on a pulse-by-pulse basis to maintain the following relationship:

$$\frac{V_{T1}}{V_{R1} + V_{T1}} = \frac{V_{T2}}{V_{R2} + V_{T2}} = \eta(cons\tan t)$$

wherein the constant η is a real number between 0.0 and 0.5 By fixing the relationship between the reflected light and transmitted light in each cavity in the two cavity designs, the incoming light can be quantitatively processed utilizing the known relationship between the signals of each cavity. A typical operating point would be for $\eta = 0.25$, thereby 25% of the light would be transmitted through the interferometer and 75% reflected, and would represent an operating point half way along each resonance curve. It is evident from FIGURE 10 that the above relationship can be satisfied for two distinct cases: either below the resonance peak or above it thereby changing the polarity of the detected signals.

The present design permits the interferometer to be self-stabilized utilizing exclusively the light which is delivered to the interferometer. Variations in the intensity of the incoming light, which typically

are associated with each minute change in positioning
of the surface being tested, have little or no impact
on the functionality of the interferometer because the
signals are based on percentages of light reflected or
5   transmitted with respect to the total amount of light,
and thus, are, in effect, normalized for the intensity
of the incoming light. It may not be necessary to
adjust the cavity tuning position on each laser pulse
depending on the drift rate of the laser and the
10   thermal stability of the interferometer. For example at
a 400Hz pulse rate adjustments could be made on every
10th pulse or even less frequently depending on the
environment and design. The present invention also
uses algorithms based on absolute light intensity to
15   suspend adjustment operations if the light level is too
low, thereby preventing erroneous adjustments when the
laser beams are off the target and tuning is
impossible. When operated in conjunction with pulsed
detection lasers it is typical that some form of peak-
20   detection circuitry be employed to hold the peak values
constant while a low-speed analog-to-digital converter
samples the two or four channels of data. The drive
voltage to each of the piezoelectric mirror mounts 876
and 976 is adjusted to compensate for any error based
25   on the previous pulse. Reset of the peak detectors
occurs prior to the next pulse. An electo-optic
intensity controller (not shown) is typically used to
limit the maximum light level sent to lens 810 and
subsequently to detectors 880, 890, 980, and 990
30   thereby preventing damage to the detectors or signal
electronics. The information used to control the light
level is extracted from the same data used to stabilize

the interferometer. Again, based on the results of the
prior pulse the appropriate voltage is projected for
the next pulse.

In the present invention having a two cavity
5   design, substantially all of the incoming light is
utilized for both stabilization and detection.
Additionally, the second cavity permits a second set of
signals that can be used to improve signal strength.

The output signal from an interferometer in
10   connection with the detection of ultrasonic surface
displacements, where the displacement u << lambda can
be represented with the following equation:

$$s(t) \quad = \quad u(t) * r(t) + a(t) * r'(t) + n(t)$$

where "s" represents the overall signal being produced
15   by the interferometer; "k" is the wavevector defined as

$k = \dfrac{2\pi}{\lambda}$; "u" represents the ultrasonic surface

displacements being measured (i.e., the desired

signal); "r-prime" represents the response function of

the interferometer; "a" represents the laser noise

20   (e.g., amplitude fluctuation); "r" represents the

response function of the interferometer to the laser

noise, which may be different from the response to an

input signal; and "n" represents noise in the detection

process (e.g., shot noise, electronic thermal noise,

25   etc.).

The complex response functions of a confocal

Fabry-Perot interferometer to an ultrasonic signal with

a frequency $\omega_u = 2\pi f_u$ or amplitude noise fluctuation

$\omega_n = 2\pi f_n$ can be defined with the following equations:

$$r_{T-\text{mode}}(\omega_u) = -i\left(\frac{\beta(\omega\tau + \omega_u\tau)}{\beta(\omega\tau)} - \frac{\overline{\beta(\omega\tau - \omega_u\tau)}}{\overline{\beta(\omega\tau)}}\right)\left(e^{-i\omega_u\frac{\tau}{4}} + R^2 e^{-i\omega_u\frac{3\tau}{4}}\right)\left(\frac{1}{1+R^2}\right)$$

5

$$r'_{T-\text{mode}}(\omega_n) = \left(\frac{\beta(\omega\tau + \omega_n\tau)}{\beta(\omega\tau)} + \frac{\overline{\beta(\omega\tau - \omega_n\tau)}}{\overline{\beta(\omega\tau)}}\right)\left(e^{-i\omega_n\frac{\tau}{4}} + R^2 e^{-i\omega_n\frac{3\tau}{4}}\right)\left(\frac{1}{1+R^2}\right)$$

$$r_{R-\text{mode}}(\omega_u) = -i\frac{\left[\overline{\gamma(\omega\tau)}\gamma(\omega\tau + \omega_u\tau) + \overline{\beta(\omega\tau)}\beta(\omega\tau + \omega_u\tau)e^{-i\omega_u\frac{\tau}{2}} - \gamma(\omega\tau)\overline{\gamma(\omega\tau + \omega_u\tau)} - \beta(\omega\tau)\overline{\beta(\omega\tau + \omega_u\tau)}e^{i\omega_u\frac{\tau}{2}}\right]}{\left[|\gamma(\omega\tau)|^2 + |\beta(\omega\tau)|^2\right]}$$

10

$$r'_{R-\text{mode}}(\omega_n) = \frac{\left[\overline{\gamma(\omega\tau)}\gamma(\omega\tau + \omega_n\tau) + \overline{\beta(\omega\tau)}\beta(\omega\tau + \omega_n\tau)e^{-i\omega_n\frac{\tau}{2}} + \gamma(\omega\tau)\overline{\gamma(\omega\tau + \omega_n\tau)} - \beta(\omega\tau)\overline{\beta(\omega\tau + \omega_n\tau)}e^{i\omega_n\frac{\tau}{2}}\right]}{\left[|\gamma(\omega\tau)|^2 + |\beta(\omega\tau)|^2\right]}$$

15

Where the same substitutions for the beta and gamma
functions as defined previously have been used to
simplify the equations. In the above equations

20   $\tau = 4r_{mirror}/c$ is the cavity round trip delay for mirrors of
radius "r_{mirror}" and c is the speed of light. Finally the
cavity tune position is defined by

$$\omega\tau = \sqrt{\frac{1-\eta}{\eta}}\left(\frac{1-R^2}{R}\right)$$

where η is the linear tune position between 0 and 0.5 as introduced previously, with 0.25 representing a position halfway along the resonance curve.

If a signal is generated for both the reflected and transmitted components of a confocal cavity, the two signals can be represented as follows:

$$S_1(t) = U_1(t) * r_1(t) + a_1(t) * r_1'(t) + n_1(t)$$

$$S_2(t) = U_2(t) * r_2(t) + a_2(t) * r_2'(t) + n_2(t)$$

where, for example, S_1 represents the light that has been transmitted through the cavity, and S_2 represents the light that has been reflected back through the cavity.

Because the input signal is the same for each formulae, $U_1 = U_2$ and $a_1 = a_2$. These relationships are true because the ultrasonic surface displacements and the laser noise are independent of the reflection and transmission modes. Therefore, the two equations can be rewritten as follows:

$$S_1(t) = U(t) * r_1(t) + a(t) * r_1'(t) + n_1(t)$$

$$S_2(t) = U(t) * r_2(t) + a(t) * r_2'(t) + n_2(t)$$

Ideally, the two modes of the cavity have the same response functions with respect to signal "u" , but the responses are negatives of each other because the transmission and reflection modes have opposite response slopes. Hence, $r_1 + r_2 = 0$. Ideally, with respect to the laser noise, $r_1' = r_2'$. Each response function must be normalized in regard to the tune position of the interferometer and is implicitly corrected to indicate a balanced response between the two modes. For example

the if the transmission tune position is at 25% then
the reflection is at 75% and a 3x normalization
correction factor is used. And, if the signals are used
to create a differential, the following relationship

5   results (dropping the time notation):

$$S_2(t) = U(t)*r_2(t) - a(t)*r_2'(t) - a(t)*r_1'(t) + n_2(t) - n_1(t)$$

Dropping the time aspect, for ease of representation,
and making the substitutions results in:

10   $$S_2 - S_2 \quad = \quad u*r_2 - u*r_1 + a*r_2' - a*r_1' + n_2 - n_1$$
$$= \quad u*r_1 - u*r_1 + a*r_1' - a*r_1' + n_2 - n_1$$
$$= \quad -2u*r_1 + n_2 - n_1$$

Hence, by using a differential signaling scheme, the
common mode laser noise can be eliminated. Even if the

15   stated conditions relating to $\{r_1, r_2\}$ and $\{r_1', r_2'\}$ are
not perfectly met, the differential signaling scheme
has the effect of removing substantially all common
mode noise "a(t)".

Further, if n_2 is uncorrelated with n_1, then the

20   two noise fluctuations will add incoherently and if the
magnitudes of the two are substantially similar,

$|n_1| = |n_2| = |n|$, we get:

$$S_2 - S_1 = 2(2k)u*r_2 + \sqrt{2}n$$

25

This is the same result one would arrive at by
considering the process of averaging two signals with
uncorrelated noise terms of equal magnitudes, where the
noise will be increase by the square-root of the number

30   of averages and the signal would increase in a linear

manner.

1.4 in addition to the removal of common-mode laser noise. Each pair of signals for the two cavities is processed in a substantially similar manner to remove common-mode noise and then the two remaining signals can be further combined yielding another 1.4 increase in SNR.

Typically, the dominate noise source is from laser relaxation oscillations in solid state lasers and is characterized by the "relative intensity noise" or "RIN" of the detection laser. Reduction or elimination of laser RIN is essential for high SNR performance. In systems employing post collection optical amplification schemes, hetrodyne-mixing noise from signal and amplified spontaneous emission ("ASE") can also manifest as a common-mode noise source. Again, use of the self-referenced differential confocal Fabry-Perot interferometer can be used to minimize or eliminate such noise terms.

FIGURE 11 demonstrates the significant improvement in SNR. In FIGURE 11 the SNR plot 1120 illustrates the limits associated when common-mode laser produced noise "RIN" is not removed. Generally, when very little light is being delivered to the interferometer, thermal noise dominates and hence limits the SNR, which limitation is illustrated by the lower portion of single cavity SNR plot 1120. As the light being delivered to the interferometer is increased, the increase in SNR rolls off and becomes laser noise limited due to "RIN" effects, which limitation is illustrated by the upper portion of single cavity SNR plot 1120. Hence, in a typical single-mode processed

confocal cavity interferometer, the SNR may at best be
75 dB. Moreover, above about 1 milliwatt, further
increases in the amount of light being delivered to the
interferometer are wasted because the laser noise
5   dominates.

FIGURE 11 also illustrates a differential SNR plot
1160, plotted as a function of optical power. As the
light being delivered to the interferometer is
increased, differential SNR plot 1160 generally
10   increases and is limited only by shot noise limit 1140
(i.e., the internal noise associated with the
detectors). Shot noise 1140 appears as a linear
function on the logarithmic scale of FIGURE 11. As
differential SNR plot 1160 demonstrates, the ability to
15   reduce the common mode laser noise results in a
significant increase in SNR, and can be as much as
30dB. Moreover, by increasing the amount of light being
delivered to the interferometer, the SNR can be
significantly improved.

20   FIGUREs 12A and 12B present a signal response
analysis for reflected signal, transmitted signal, and
a combination of the two. FIGURE 12A is a plot
representative of the SNR of these signals as a
function of frequency, while FIGURE 12B presents the
25   relative phase diagrams for each the reflected signal
and transmitted signal, again as a function of
frequency. These signals are related to $r_1(t)$ and $r_2(t)$,
respectively, discussed above. These plots were
generated using a confocal cavity having spherical
30   mirrors that are 95% reflective spaced one (1.0) meter
apart. FIGURE 12A demonstrates that the SNR of the
combined reflected and transmitted signal generally is

higher than either component alone. FIGURE 12B
illustrates that over the frequency range on the
abscissa, the phase difference between the transmitted
signal and reflected signal changes gradually from.
approximately 180 degrees (i.e., completely out of
phase) and levels out to approximately 90 degrees.
Differences in phase must be considered when combining
the transmitted and reflected signals from the
cavities. This shows the expected result where at low
frequency the response to signals follows the dc-
response curve in FIGURE 10, which clearly would
represent a 180-degree phase shift between the two
modes. The response at high frequencies is somewhat
more complicated but is a known function as defined
previously and can be deconvoluted from the measured
signals for optimal processing results.

FIGUREs 13A and 13B presents a noise response
analysis for the interferometer's response to laser
noise. FIGURE 13A is a plot representative of the
magnitude of reflected noise response and transmitted
noise response as a function of frequency, while FIGURE
13B presents the relative phase diagrams for the
reflected noise and transmitted noise, again as a
function of frequency. These plots were generated
using a confocal cavity having spherical mirrors that
are 95% reflective and being spaced one (1.0) meter
apart. FIGURE 13A demonstrates that for most
frequencies, more noise is reflected than transmitted
through the cavity. FIGURE 13B illustrates that over
the frequency range on the abscissa, the phase
difference between the transmitted noise and reflected
noise changes gradually from approximately 0 degrees

(i.e., completely in phase) and levels out to
approximately 90 degrees. Differences in phase must be
considered when combining these outputs from the
cavities.

5   FIGUREs 14A represents a modified signal analysis,
wherein the transmitted and reflected components have
been modified to permit cancellation of the noise when
the two components are subtracted. FIGURE 14B
illustrates that over most frequencies, the phase
10   difference between the modified transmitted signal and
reflected signal remains relatively constant at
approximately 180 degrees (i.e., completely out of
phase). This allows the two components to be subtracted
for optimum noise reduction, while maintaining a
15   significant level of signal. These plots show that
transforming the data for maximum noise cancellation
has the added benefit that signal is also improved.

       In another embodiment of the present invention,
the two confocal Fabry-Perot cavities can be self-
20   referenced stabilized entirely with light present on
the signal detectors such that the corresponding pair
of transmitted and reflected intensities represent
inverted responses to signals, yet remain in-phase to
amplitude noise. This has the added advantage of
25   removing common-mode noise without detailed knowledge
of either the signal or noise response functions due to
the substantially matched responses between the
reflection and transmission for each cavity. Again, the
resulting SNR enhanced pair of signals can be further
30   combined to one signal, using the appropriate
corrections for optimally combining the processed
reflected and transmitted signals.

In one embodiment of the interferometer of the
current apparatus, the detectors and the electronic
circuitry used to monitor and adjust the cavities are
integrated into the interferometer. When the detectors
5   are integrated into the interferometer, there is a
potential for introducing noise because the ground
plane for the detector circuitry is separate from the
ground plane for the data acquisition apparatus, and
though the two planes may be connected, the distance
10   between them permits the introduction of unwanted
noise.

FIGURE 15 illustrates an alternative embodiment of
an interferometer which is purely optical, and the
detectors and the control circuitry are external,
15   sharing a common ground plane with the data acquisition
apparatus. In FIGURE 15, the phase-modulated light is
collected from the target and fed via fiber optics into
electro-optical assembly 1500 comprised of optical
amplifier 1510, optical interferometer 1520, and
20   control electronics 1580. Optical interferometer 1520
is characterized by optical input and a plurality of
optical outputs, though only one is shown in FIGURE 15
for simplicity of presentation.

The output from optical interferometer 1520 is fed
25   to a plurality of detectors 1540 which convert the
optical input to analog signaling. The analog signaling
is conditioned by analog signal conditioner 1550 and
then captured and processed by digital signal

processing ("DSP") unit 1560. DSP unit 1560 will
30   compare V_{R1} relative to $V_{r1} + V_{T1}$ and V_{R2} relative to $V_{R2} +$
V_{T2} and determine whether adjustments are required in
the cavities of optical interferometer 1520 to maintain

the desired relationships, as previously discussed. If
adjustments are required, then a digital output from
DSP unit 1560 may be converted to analog by D/A unit
1570 and sent to electronic controller 1580, which
5   makes the proper adjustments to optical interferometer
1520, for example, by adjusting the piezoelectric
devices within the interferometer.

      Optical amplifier 1510 functions on a pulse-by-
pulse basis, and hence, a trigger signal is used in
10   operation. The trigger signal may be provided
indirectly, for example, through power supply 1590, or
may be provided directly to optical amplifier 1510. In
a real-time like fashion, the electronics process the
optical signal to determine the amount of light that
15   has been delivered to the interferometer. If the
interferometer is saturated, then the gain is turned
down inside optical amplifier 1510, and the
interferometer is adjusted to operate in a more optimum
range. If the interferometer is operating below an
20   optimum light level, then the gain is turned up inside
optical amplifier 1510, and the interferometer is again
adjusted to operate in a more optimum range. As
illustrated previously in FIGURE 11, the SNR in the
present design can be improved by increasing the light
25   delivered to the interferometer. Increasing SNR is
usually desirable. Moreover, because the stabilization
scheme of the interferometer is independent of light
intensity, varying the optical gain has little or no
effect on the stabilization process of the
30   interferometer.

      FIGURE 16 illustrates an electrical schematic for
an improved detector. The detector must accommodate two

very different inputs: 1) the large detection pulse;
and 2) the tiny modulations riding on top of said
pulse, containing information about the ultrasonic
surface displacements. The large detection pulse must
5   be converted into a dc signal so that the
interferometer can be stabilized, while the tiny
modulations must be separated for demodulation. The
improved detector of FIGURE 16 accommodates these two
different signals with a single circuit through the use
10   of a "T-feedback" loop, said "T" being formed by
resistors R1, R2 and R3. This circuit provides a low
gain response to the large pulse and a high gain
response to the modulations.

　　　FIGURE 17 illustrates the frequency response of
15   the T-feedback loop.

　　　While circuits other than those illustrated by
FIGURE 16 can be used to meet these needs, the circuit
provided in FIGURE 16 is a single circuit solution to
the problem.

20   　　　Although the present invention has been described
in detail, it should be understood that various
changes, substitutions and alterations can be made
hereto without departing from the spirit and scope of
the invention as defined by the appended claims.